

BR2300-VND9

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC)

Supported bill VND 1000, 2000, 5000, 10000, 20000
50000, 100000, 200000, 500000 9 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject VND 1000 & 2000 (Note.2)	ON									
★	Accept VND 1000 & 2000 (Note.2)	OFF									
★	Reject VND 5000 & 10000 & 20000 & 50000		ON								
★	Accept VND 5000 & 10000 & 20000 & 50000		OFF								
★	Reject VND 100000 & 200000 & 500000			ON							
★	Accept VND 100000 & 200000 & 500000			OFF							
★	High Acceptance (Note.4)				ON						
★	High Security				OFF						
★	MDB Display Setting(See Table 1)(MDB Only)					ON					
★	MDB Display Setting(See Table 1)(MDB Only)					OFF					
★	Normal						OFF	OFF			
★	Load Banknote to Recycle						ON	OFF			
★	Load Banknote to Stacker						OFF	ON			
★	Unload Banknote to Stacker						ON	ON			
★	MDB Display Setting(See Table 1)(MDB Only)								ON		
★	MDB Display Setting(See Table 1)(MDB Only)								OFF		
★	ICT-BC Mode									ON	
★	MDB Mode									OFF	
★	MDB Mode										
★	Virtual MDB Recycler Function (Note.1)										ON
★	Standard MDB Recycler Function										OFF

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Recycled Banknote represents virtual MDB coin type.

Note.2:** MDB Mode:

When Dip 1 is OFF, Reject VND 500000.

When Dip 1 is ON, Accept VND 500000.

Note.3: calibrate card.

Note.4: High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Note.5: Normal:Scaling Factor (SF) = 1

Decimal Point Position (DPP) = 0

Note.6: The function(credit divide by1000) is only used at standard MDB recycler mode

Note.7: The function(credit divide by100) is only used at standard MDB recycler mode

BR2300 - VND9 (MDB/ICT-BC)

Currency Assign Data

Interface Bill value	ICT-BC	MDB					
		When Dip 1 is OFF			When Dip 1 is ON		
		Note.5	Note.6	Note.7	Note.5	Note.6	Note.7
BV1	VND 1000	VND 1000	VND 1	VND 10	VND 5000	VND 5	VND 50
BV2	VND 2000	VND 2000	VND 2	VND 20	VND 10000	VND 10	VND 100
BV3	VND 5000	VND 5000	VND 5	VND 50	VND 20000	VND 20	VND 200
BV4	VND 10000	VND 10000	VND 10	VND 100	VND 50000	VND 50	VND 500
BV5	VND 20000	VND 20000	VND 20	VND 200	VND 100000	VND 100	VND 1000
BV6	VND 50000	VND 50000	VND 50	VND 500	VND 200000	VND 200	VND 2000
BV7	VND 100000	VND 100000	VND 100	VND 1000	VND 500000	VND 500	VND 5000
BV8	VND 200000	VND 200000	VND 200	VND 2000			
BV9	VND 500000						

Note.5: Normal:Scaling Factor (SF) = 1

Decimal Point Position (DPP) = 0

Note.6: The function(credit divide by1000) is only used at standard MDB recycler mode

Note.7: The function(credit divide by100) is only used at standard MDB recycler mode

Table 1

	Sw5	Sw8
★ Normal Credit (Note.5)	OFF	OFF
Credit divide by 1000 (Note.6)	OFF	ON
Credit divide by 100 (Note.7)	ON	OFF
Reserved	ON	ON