

BRV-MXN9(MXN5+USD4)

BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy)

Supported bill MXN 20, 50, 100, 200, 500 5bills. USD 1, 5, 10, 20 4bills.

BRV dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject USD 1	ON											
★	Accept USD 1	OFF											
★	Reject MXN 50 & USD 5		ON										
★	Accept MXN 50 & USD 5		OFF										
★	Reject MXN 100 & USD 10			ON									
★	Accept MXN 100 & USD 10			OFF									
★	Reject MXN 200/500 & USD 20			ON									
★	Accept MXN 200/500 & USD 20			OFF									
★	Reject MXN 20				ON								
★	Accept MXN 20				OFF								
★	Normal					OFF	OFF						
	Load Banknote to Recycle					ON	OFF						
	Load Banknote to Stacker					OFF	ON						
	Unload Banknote to Stacker					ON	ON						
	Accept Mexico Pesos and US Dollars (Note.3)								ON				
★	Accept Mexico Pesos Only (Note.3)								OFF				
	MDB Mode	SW1	SW2	SW3	SW4	JPSTD Dummy Mode							
	Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON				
★	Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF				
	Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF				
★	Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF				
	Reserved			ON		4 Bank Note Limitation Per Transaction	ON	ON	OFF				
★	Reserved				ON	5 Bank Note Limitation Per Transaction	OFF	OFF	ON				
★	Reserved				OFF	6 Bank Note Limitation Per Transaction	ON	OFF	ON				
	Virtual MDB Recycler Function (Note.5)				ON	No Refund After the Deal						ON	
★	Standard MDB Recycler Function				OFF	★ Refund After the Deal						OFF	

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) For Accepting US Dollars, make sure you have dip 8 set to ON position.

(* Exchange Rate on USD to MXN is 1:18 for MDB,ICT-BC Mode)

(4) Calibration card is needed.

(5) Recycled Banknote represents virtual MDB coin type.

BRV-MXN9(MXN5+USD4)(ICT-BC/MDB/JPSTD Dummy)

Interface Settings: 2(ICT-BC)

	INTERFACE	SW5	SW6	SW7	SW8
★	Reserved	ON			
★	Reserved	OFF			
★	Connect with MDB Connector		ON		
★	Connect with RS232 Connector		OFF		
	MDB Mode			OFF	OFF
	JPSTD Dummy Mode			OFF	ON
	Reserved			ON	OFF
★	ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(JPSTD Dummy)

	INTERFACE	SW5	SW6	SW7	SW8
★	Escrow (JPSTD Dummy Mode)	ON			
★	No Escrow (JPSTD Dummy Mode)	OFF			
	Reserved		ON		
★	Reserved		OFF		
	MDB Mode			OFF	OFF
★	JPSTD Dummy Mode			OFF	ON
	Reserved			ON	OFF
	ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

	INTERFACE	SW5	SW6	SW7	SW8
★	Scaling Factor (SF)= 100 Decimal Point Position (DPP)= 2	ON			
	Scaling Factor (SF)= 1 Decimal Point Position (DPP)= 0	OFF			
	Reserved		ON		
★	Reserved		OFF		
★	MDB Mode			OFF	OFF
	JPSTD Dummy Mode			OFF	ON
	Reserved			ON	OFF
	ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	JPSTD Dummy	ICT-BC	MDB	Recycler banknote inventory	
BV1	MXN 20	MXN 20	MXN 20	MXN 20	25 pcs
BV2	MXN 50	MXN 50	MXN 50	MXN 50	25 pcs
BV3	MXN 100	MXN 100	MXN 100	MXN 100	25 pcs
BV4	MXN 200	MXN 200	MXN 200	MXN 200	25 pcs
BV5	MXN 500	MXN 500	MXN 500	MXN 500	25 pcs
BV6	USD 1	USD 1	USD 1	USD 1	25 pcs
BV7	USD 5	USD 5	USD 5	USD 5	25 pcs
BV8	USD 10	USD 10	USD 10	USD 10	25 pcs
BV9	USD 20	USD 20	USD 20	USD 20	25 pcs