

BRV-RON2

BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy)

Supported bill RON 1, 5 2bills.

BRV dip-switch settings and functions:

| | FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 |
|---|---|-----|-----|-----|-----|--|-----|-----|-----|-----|-----|-----|-----|
| | Reject RON 1 | ON | | | | | | | | | | | |
| ★ | Accept RON 1 | OFF | | | | | | | | | | | |
| | Reject RON 5 | | ON | | | | | | | | | | |
| ★ | Accept RON 5 | | OFF | | | | | | | | | | |
| | Reserved | | | ON | | | | | | | | | |
| ★ | Reserved | | | OFF | | | | | | | | | |
| | Reserved | | | ON | | | | | | | | | |
| ★ | Reserved | | | OFF | | | | | | | | | |
| | Reserved | | | | ON | | | | | | | | |
| ★ | Reserved | | | | OFF | | | | | | | | |
| ★ | Normal | | | | | OFF | OFF | | | | | | |
| | Load Banknote to Recycle | | | | | ON | OFF | | | | | | |
| | Load Banknote to Stacker | | | | | OFF | ON | | | | | | |
| | Unload Banknote to Stacker | | | | | ON | ON | | | | | | |
| | Reserved | | | | | | | | ON | | | | |
| ★ | Reserved | | | | | | | | OFF | | | | |
| | MDB Mode | SW1 | SW2 | SW3 | SW4 | JPSTD Dummy Mode | | | | | | | |
| | Reserved | ON | | | | ★ 255 Bank Note Limitation Per Transaction | ON | ON | ON | | | | |
| ★ | Reserved | OFF | | | | 1 Bank Note Limitation Per Transaction | OFF | OFF | OFF | | | | |
| | Reserved | | ON | | | 2 Bank Note Limitation Per Transaction | ON | OFF | OFF | | | | |
| ★ | Reserved | | OFF | | | 3 Bank Note Limitation Per Transaction | OFF | ON | OFF | | | | |
| | Reserved | | | | | 4 Bank Note Limitation Per Transaction | ON | ON | OFF | | | | |
| | Reserved | | | | | 5 Bank Note Limitation Per Transaction | OFF | OFF | ON | | | | |
| ★ | Reserved | | | | | 6 Bank Note Limitation Per Transaction | ON | OFF | ON | | | | |
| | Reserved | | | | | 7 Bank Note Limitation Per Transaction | OFF | ON | ON | | | | |
| | Virtual MDB Recycler Function (Note.4) | | | | ON | No Refund After the Deal | | | | | | ON | |
| ★ | Standard MDB Recycler Function | | | | OFF | ★ Refund After the Deal | | | | | | OFF | |

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) Calibrate card is needed.

(4) Recycked Banknote represents virtual MDB coin type.

BRV-RON2(ICT-BC/MDB/JPSTD Dummy)

Interface Settings: 2(ICT-BC)

| | INTERFACE | SW5 | SW6 | SW7 | SW8 |
|---|------------------------------|-----|-----|-----|-----|
| | Reserved | ON | | | |
| ★ | Reserved | OFF | | | |
| | Connect with MDB Connector | | ON | | |
| ★ | Connect with RS232 Connector | | OFF | | |
| | MDB Mode | | | OFF | OFF |
| | JPSTD Dummy Mode | | | OFF | ON |
| | Reserved | | | ON | OFF |
| ★ | ICT-BC Mode | | | ON | ON |

★ Manufacture setting

Interface Settings: 2(JPSTD Dummy)

| | INTERFACE | SW5 | SW6 | SW7 | SW8 |
|---|------------------------------|-----|-----|-----|-----|
| | Escrow (JPSTD Dummy Mode) | ON | | | |
| ★ | No Escrow (JPSTD Dummy Mode) | OFF | | | |
| | Reserved | | ON | | |
| ★ | Reserved | | OFF | | |
| | MDB Mode | | | OFF | OFF |
| ★ | JPSTD Dummy Mode | | | OFF | ON |
| | Reserved | | | ON | OFF |
| | ICT-BC Mode | | | ON | ON |

★ Manufacture setting

Interface Settings: 2(MDB)

| | INTERFACE | SW5 | SW6 | SW7 | SW8 |
|---|---|-----|-----|-----|-----|
| ★ | Scaling Factor (SF)= 100 Decimal Point Position (DPP)= 2 | ON | | | |
| | Scaling Factor (SF)= 1 Decimal Point Position (DPP)= 0 | OFF | | | |
| | Reserved | | ON | | |
| ★ | Reserved | | OFF | | |
| ★ | MDB Mode | | | OFF | OFF |
| | JPSTD Dummy Mode | | | OFF | ON |
| | Reserved | | | ON | OFF |
| | ICT-BC Mode | | | ON | ON |

★ Manufacture setting

Currency Assign Data

| Interface Bill value | JPSTD Dummy | ICT-BC | MDB | Recycler banknote inventory | |
|-------------------------|-------------|--------|-------|--------------------------------|--------|
| BV1 | RON 1 | RON 1 | RON 1 | RON 1 | 40 pcs |
| BV2 | RON 5 | RON 5 | RON 5 | RON 5 | 35 pcs |