

GSP2 (GBP+SCO)

L77-P3/P6 L77F-P2/P5 DIP SWITCHES SETTING : 1(Pulse/ICT/MDB)

Supported bill

English banknotes: England £ 5, £ 10

Scottish banknotes:

Royal Bank & Bank of Scotland & Clydesdale Bank £ 5, £ 10

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / £ 5	OFF	OFF	OFF							
2 Pulse / £ 5	OFF	OFF	ON							
3 Pulse / £ 5	OFF	ON	OFF							
4 Pulse / £ 5	OFF	ON	ON							
5 Pulse / £ 5	ON	OFF	OFF							
10 Pulse / £ 5	ON	OFF	ON							
20 Pulse / £ 5	ON	ON	OFF							
100 Pulse / £ 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept £ 5						ON				
Reject £ 5						OFF				
★ Accept £ 10							ON			
Reject £ 10							OFF			
★ Reserved							ON			
Reserved							OFF			
★ Reserved								ON		
Reserved								OFF		
★ Reserved									ON	
Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L77-GSP2 P3/P6 L77F-GSP2 P2/P5 (Pulse/ICT/MDB)

DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT Interface		OFF	ON	
MDB Mode		ON	ON	
Reserved				ON
				OFF

★ Manufacture setting

Interface Bill value	ICT	Pulse	MDB
BV1	£ 5	£ 5	£ 5
BV2	£ 10	£ 10	£ 10

DIP SWITCHES SETTING : 2(ICT)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT Interface		OFF	ON	
MDB Mode		ON	ON	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT Interface		OFF	ON	
★ MDB Mode		ON	ON	
Reserved				ON
				OFF

★ Manufacture setting