

BYR7**L77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/MDB)**

Supported bill Ruble 500, 1000, 5000, 10000, 20000,
50000, 100000 7bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Ruble 500	OFF	OFF	OFF							
	2 Pulse / Ruble 500	OFF	OFF	ON							
	3 Pulse / Ruble 500	OFF	ON	OFF							
	4 Pulse / Ruble 500	OFF	ON	ON							
	5 Pulse / Ruble 500	ON	OFF	OFF							
	10 Pulse / Ruble 500	ON	OFF	ON							
	20 Pulse / Ruble 500	ON	ON	OFF							
	100 Pulse / Ruble 500	ON	ON	ON							
	Fast output Pulse Lo= 50ms 										

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L77-BYR7(Pulse/MDB)**DIP SWITCHES SETTING : 2(Pulse)**

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	MDB Mode		OFF		
★	Reserved			ON	
				OFF	
★					ON
★					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 10 Decimal Point Position (DPP) = 1	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	MDB Interface		OFF		
★	Normal			ON	
	Credit divided by 100			OFF	
★	Reserved				ON
					OFF

★ Manufacture setting