

UYU6

L77&L77F-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill \$ 20, 50, 100, 200, 500, 1000 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / \$ 10	OFF	OFF	OFF							
2 Pulse / \$ 10	OFF	OFF	ON							
3 Pulse / \$ 10	OFF	ON	OFF							
4 Pulse / \$ 10	OFF	ON	ON							
5 Pulse / \$ 10	ON	OFF	OFF							
10 Pulse / \$ 10	ON	OFF	ON							
20 Pulse / \$ 10	ON	ON	OFF							
100 Pulse / \$ 10	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low				ON						
★ Inhibit level Active High				OFF						
★ Accept \$ 20						ON				
Reject \$ 20						OFF				
★ Accept \$ 50							ON			
Reject \$ 50							OFF			
★ Accept \$ 100								ON		
Reject \$ 100								OFF		
★ Accept \$ 200									ON	
Reject \$ 200									OFF	
★ Accept \$ 500 & 1000										ON
Reject \$ 500 & 1000										OFF

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode				
ICT002U Interface Mode		OFF		
Reserved				
★ Reserved			OFF	
Reserved			ON	
★ Reserved			OFF	

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	\$ 20	\$ 20
BV2	\$ 50	\$ 50
BV3	\$ 100	\$ 100
BV4	\$ 200	\$ 200
BV5	\$ 500	\$ 500
BV6	\$ 1000	\$ 1000

★ Manufacture setting

Appendix