

L77F/PL77-TWD4

L77F&PL77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill TWD 100, 200, 500, 1000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / TWD 100	OFF	OFF	OFF							
	2 Pulse / TWD 100	OFF	OFF	ON							
	3 Pulse / TWD 100	OFF	ON	OFF							
	4 Pulse / TWD 100	OFF	ON	ON							
	5 Pulse / TWD 100	ON	OFF	OFF							
	10 Pulse / TWD 100	ON	OFF	ON							
	20 Pulse / TWD 100	ON	ON	OFF							
	100 Pulse / TWD 100	ON	ON	ON							
★	Fast output Pulse Lo= 50ms Hi=100ms				ON						
	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept TWD 100						ON				
	Reject TWD 100						OFF				
★	Accept TWD 200							ON			
	Reject TWD 200							OFF			
★	Accept TWD 500								ON		
	Reject TWD 500								OFF		
★	Accept TWD 1000									ON	
	Reject TWD 1000									OFF	
★	Reserve										ON
	Reserve										OFF

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2 Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	★ Pulse Mode		ON		
	ICT104U Interface Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

Interface Bill value	ICT104U	Pulse
BV1	TWD 100	TWD 100
BV2	TWD 200	TWD 200
BV3	TWD 500	TWD 500
BV4	TWD 1000	TWD 1000

★ Manufacture setting

Appendix