

# L77F&PL77-JPY4

## L77F&PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill ¥ 1000, 2000, 5000, 10000 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / ¥ 1000	OFF	OFF	OFF							
2 Pulse / ¥ 1000	OFF	OFF	ON							
3 Pulse / ¥ 1000	OFF	ON	OFF							
4 Pulse / ¥ 1000	OFF	ON	ON							
5 Pulse / ¥ 1000	ON	OFF	OFF							
10 Pulse / ¥ 1000	ON	OFF	ON							
20 Pulse / ¥ 1000	ON	ON	OFF							
100 Pulse / ¥ 1000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept ¥ 1000						ON				
Reject ¥ 1000						OFF				
★ Accept ¥ 2000							ON			
Reject ¥ 2000							OFF			
★ Accept ¥ 5000								ON		
Reject ¥ 5000								OFF		
★ Accept ¥ 10000									ON	
Reject ¥ 10000									OFF	
Reserved										ON
★ Reserved										OFF

## DIP SWITCHES SETTING : 2 Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode	Pulse Mode		ON	
ICT104U Interface Mode	★ ICT104U Interface Mode		OFF	
★ Reserved			ON	
			OFF	
				ON
				OFF

Interface Bill value	ICT104U	Pulse
BV1	¥ 1000	¥ 1000
BV2	¥ 2000	¥ 2000
BV3	¥ 5000	¥ 5000
BV4	¥ 10000	¥ 10000

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.  
(2)Dip switches 1 to 5 are only used for pulse protocol.