



**BYR7**

**L83 DIP SWITCHES SETTING : 1(Pulse/ICT)**

**Supported bill Ruble 500, 1000, 5000, 10000, 20000,  
50000, 100000 7bills.**

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Ruble 500	OFF	OFF	OFF							
2 Pulse / Ruble 500	OFF	OFF	ON							
3 Pulse / Ruble 500	OFF	ON	OFF							
4 Pulse / Ruble 500	OFF	ON	ON							
5 Pulse / Ruble 500	ON	OFF	OFF							
10 Pulse / Ruble 500	ON	OFF	ON							
20 Pulse / Ruble 500	ON	ON	OFF							
100 Pulse / Ruble 500	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Ruble 500 & 1000						ON				
Reject Ruble 500 & 1000						OFF				
★ Accept Ruble 5000 & 10000							ON			
Reject Ruble 5000 & 10000							OFF			
★ Accept Ruble 20000								ON		
Reject Ruble 20000								OFF		
★ Accept Ruble 50000									ON	
Reject Ruble 50000									OFF	
★ Accept Ruble 100000										ON
Reject Ruble 100000										OFF

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

## **L83-BYR7(Pulse/ICT)**

### **DIP SWITCHES SETTING : 2(Pulse)**

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT Protocol Mode		OFF		
★	Reserved			ON	
				OFF	
★					ON
					OFF

★ Manufacture setting

### **DIP SWITCHES SETTING : 3(ICT)**

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON		
	ICT Protocol Mode		OFF		
★	Reserved			ON	
				OFF	
★					ON
					OFF

★ Manufacture setting