

L83-EUR6

L83/P3/P6 DIP SWITCHES SETTING : 1(1CT104U/MDB/RS232 A0)

Supported bill EUR 5, 10, 20, 50, 100, 200 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reserved	ON									
	Reserved	OFF									
	Reserved		ON								
★	Reserved		OFF								
	Reserved			ON							
★	Reserved			OFF							
	Reserved				ON						
★	Reserved				OFF						
	Reserved					ON					
★	Reserved					OFF					
	Accept EUR 5 & 10						ON				
	Reject EUR 5 & 10						OFF				
★	Accept EUR 20 & 50							ON			
	Reject EUR 20 & 50							OFF			
★	Accept EUR 100								ON		
	Reject EUR 100								OFF		
★	Accept EUR 200									ON	
	Reject EUR 200									OFF	
★	Accept Normal										ON
	Reject EUR 5(2002) & 10(2002)										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

Currency Assign Data

Interface Bill value	MDB	RS232 A0	1CT104U
BV1	EUR 5	EUR 5	EUR 5
BV2	EUR 10	EUR 10	EUR 10
BV3	EUR 20	EUR 20	EUR 20
BV4	EUR 50	EUR 50	EUR 50

Interface Bill value	MDB	RS232 A0	1CT104U
BV5	EUR 100	EUR 100	EUR 100
BV6	EUR 200	EUR 200	EUR 200

L83-EUR6(1CT104U/MDB/RS232 A0)

DIP SWITCHES SETTING : 2(1CT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	MDB Mode		ON	ON	
	RS232 A0 Mode		ON	OFF	
★	1CT104U Interface		OFF	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★	MDB Mode		ON	ON	
	RS232 A0 Mode		ON	OFF	
	1CT104U Interface		OFF	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	MDB Mode		ON	ON	
★	RS232 A0 Mode		ON	OFF	
	1CT104U Interface		OFF	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

RS232 A0 INFORMATION	
BillType Data	
Code	Denomination
1	Reserved
2	EUR 5
3	EUR 10
4	EUR 20
5	EUR 50
6	EUR 100
7	EUR 200
8	Reserved