

L83-RO8

L83 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill RON 1, 5, 10, 20, 50, 100, 200, 500 8 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / RON 1	OFF	OFF	OFF							
	2 Pulse / RON 1	OFF	OFF	ON							
	3 Pulse / RON 1	OFF	ON	OFF							
	4 Pulse / RON 1	OFF	ON	ON							
	5 Pulse / RON 1	ON	OFF	OFF							
	10 Pulse / RON 1	ON	OFF	ON							
	20 Pulse / RON 1	ON	ON	OFF							
	100 Pulse / RON 1	ON	ON	ON							
	Fast output Pulse Hi= 65ms Lo= 85ms				ON						
★	Slow output Pulse Hi= 100ms Lo= 150ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept RON 1					ON					
	Reject RON 1					OFF					
★	Accept RON 5						ON				
	Reject RON 5						OFF				
★	Accept RON 10 & 20							ON			
	Reject RON 10 & 20							OFF			
★	Accept RON 50 & 100								ON		
	Reject RON 50 & 100								OFF		
★	Accept RON 200 & 500									ON	
	Reject RON 200 & 500									OFF	

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104U Protocol Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	RON 1	RON 1
BV2	RON 5	RON 5
BV3	RON 10	RON 10
BV4	RON 50	RON 50
BV5	RON 100	RON 100
BV6	RON 200	RON 200
BV7	RON 500	RON 500
BV8	RON 20	RON 20