

UGX6

L83 DIP SWITCHES SETTING : 1(Pulse/ICT/RS232 A0)

Supported bill UGX 1000, 2000, 5000, 10000, 20000, 50000 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / UGX 1000	OFF	OFF	OFF							
2 Pulses / UGX 1000	OFF	OFF	ON							
3 Pulses / UGX 1000	OFF	ON	OFF							
4 Pulses / UGX 1000	OFF	ON	ON							
5 Pulses / UGX 1000	ON	OFF	OFF							
10 Pulses / UGX 1000	ON	OFF	ON							
20 Pulses / UGX 1000	ON	ON	OFF							
100 Pulses / UGX 1000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept UGX 1000 & 2000						ON				
Reject UGX 1000 & 2000						OFF				
★ Accept UGX 5000							ON			
Reject UGX 5000							OFF			
★ Accept UGX 10000								ON		
Reject UGX 10000								OFF		
★ Accept UGX 20000									ON	
Reject UGX 20000									OFF	
★ Accept UGX 50000										ON
Reject UGX 50000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.
(2) Dip switches 1 to 5 are only for Pulse mode.

L83-UGX6(Pulse/ICT/RS232 A0)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
RS232 A0 Mode		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
RS232 A0 Mode		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
★ RS232 A0 Mode		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	RS232 A0	Pulse	ICT
BV1	UGX 1000	UGX 1000	UGX 1000
BV2	UGX 2000	UGX 2000	UGX 2000
BV3	UGX 5000	UGX 5000	UGX 5000
BV4	UGX 10000	UGX 10000	UGX 10000
BV5	UGX 20000	UGX 20000	UGX 20000
BV6	UGX 50000	UGX 50000	UGX 50000