

NE77-MYR6

NE77/P2/P5 DIP SWITCHES SETTING : (Pulse/ICT104U)

Supported bill MYR 1, 5, 10, 20, 50, 100 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10								
★	1 Pulse / MYR 1	OFF	OFF																
	2 Pulse / MYR 1	OFF	ON																
	5 Pulse / MYR 1	ON	OFF																
	10 Pulse / MYR 1	ON	ON																
★	Fast output Pulse Lo= 50ms Hi=100ms			ON															
	Slow output Pulse Lo= 50ms Hi=300ms			OFF															
	Inhibit level Active Low											ON							
	Inhibit level Active High											OFF							
	Accept MYR 1 & 5											ON							
	Reject MYR 1 & 5											OFF							
	Accept MYR 10 & 20											ON							
	Reject MYR 10 & 20											OFF							
	Accept MYR 50 & 100											ON							
	Reject MYR 50 & 100											OFF							
	Pluse Normal High											ON							
	Pluse Normal Low											OFF							
	Pulse Mode											ON							
	ICT104U Mode											OFF							
	★	Reserved										ON							
		Reserved										OFF							

(★) Manufacture setting

Note.(1) Please reset the bill acceptor after any changes on Dip switch.

Currency Assign Data

Interface Bill value	Pulse	ICT104U
BV1	MYR 1	MYR 1
BV2		
BV3	MYR 5	MYR 5
BV4	MYR 10	MYR 10
BV5	MYR 50	MYR 50
BV6	MYR 100	MYR 100
BV7	MYR 20	MYR 20