

## NK682-KRW4

### NK682 DIP SWITCHES SETTING : 1(Pulse/ICT104)

Supported bill KRW 1000, 5000, 10000, 50000 4bills.

|   | FUNCTION                                  | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|-------------------------------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ | 1 Pulse / KRW 1000                        | OFF | OFF |     |     |     |     |     |     |     |      |
|   | 2 Pulse / KRW 1000                        | ON  | OFF |     |     |     |     |     |     |     |      |
|   | 5 Pulse / KRW 1000                        | OFF | ON  |     |     |     |     |     |     |     |      |
|   | 10 Pulse / KRW 1000                       | ON  | ON  |     |     |     |     |     |     |     |      |
| ★ | Accept KRW 1000                           |     |     | ON  |     |     |     |     |     |     |      |
|   | Reject KRW 1000                           |     |     | OFF |     |     |     |     |     |     |      |
| ★ | Accept KRW 5000                           |     |     | ON  |     |     |     |     |     |     |      |
|   | Reject KRW 5000                           |     |     | OFF |     |     |     |     |     |     |      |
| ★ | Accept KRW 10000                          |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject KRW 10000                          |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept KRW 50000                          |     |     |     |     | ON  |     |     |     |     |      |
|   | Reject KRW 50000                          |     |     |     |     | OFF |     |     |     |     |      |
| ★ | Enable Output Sensor Detect               |     |     |     |     |     | ON  |     |     |     |      |
|   | Disable Output Sensor Detect              |     |     |     |     |     | OFF |     |     |     |      |
|   | Fast output Pulse<br>Lo= 50ms<br>Hi=100ms |     |     |     |     |     | ON  |     |     |     |      |
| ★ | Slow output Pulse<br>Lo=100ms<br>Hi=200ms |     |     |     |     |     | OFF |     |     |     |      |
| ★ | Pulse Mode                                |     |     |     |     |     |     | ON  |     |     |      |
|   | ICT104 Mode                               |     |     |     |     |     |     | OFF |     |     |      |
|   | Reserved                                  |     |     |     |     |     |     |     |     |     | ON   |
| ★ | Reserved                                  |     |     |     |     |     |     |     |     |     | OFF  |

(★) Manufacture setting

## Currency Assign Data

| Interface<br>Bill value | Pulse     | ICT104    |
|-------------------------|-----------|-----------|
| BV1                     | KRW 1000  | KRW 1000  |
| BV2                     | KRW 5000  | KRW 5000  |
| BV3                     | KRW 10000 | KRW 10000 |
| BV4                     | KRW 50000 | KRW 50000 |