

KRW4

NK682T DIP SWITCHES SETTING : 1(Pulse/ICT104)

Supported bill ₩ 1000, 5000, 10000, 50000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10						
★	1 Pulse / W 1000	OFF	OFF														
	5 Pulse / W 1000	ON	OFF														
	10 Pulse / W 1000	OFF	ON														
	15 Pulse / W 1000	ON	ON														
★	Accept W 1000			ON													
	Reject W 1000			OFF													
★	Accept W 5000				ON												
	Reject W 5000				OFF												
★	Accept W 10000					ON											
	Reject W 10000					OFF											
★	Accept W 50000						ON										
	Reject W 50000						OFF										
★	Enable Output Sensor Detect								ON								
	Disable Output Sensor Detect								OFF								
★	Fast output Pulse Lo= 50ms Hi=100ms								ON								
	Slow output Pulse Lo=100ms Hi=200ms								OFF								
★	Pulse Mode										ON						
	ICT104 Mode										OFF						
	Manufacture Default										ON						
★	System Default										OFF						

(★) Manufacture setting

Currency Assign Data

Interface Bill value	ICT104	Pulse
BV1	₩ 1000	₩ 1000
BV2	₩ 5000	₩ 5000
BV3	₩ 10000	₩ 10000
BV4	₩ 50000	₩ 50000