

NK77-LAK8

NK77 DIP SWITCHES SETTING : (Pulse/Out of Service/ICT10A)

Supported bill LAK 500, 1000, 2000, 5000, 10000, 20000, 50000, 100000 8bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / LAK 500	OFF	OFF								
	2 Pulse / LAK 500	OFF	ON								
	5 Pulse / LAK 500	ON	OFF								
	10 Pulse / LAK 500	ON	ON								
★	Enable Fish Stop			ON							
	Disable Fish Stop			OFF							
★	Inhibit level Active Low				ON						
	Inhibit level Active High				OFF						
★	Accept LAK 500 & 1000 & 2000 & 5000					ON					
	Reject LAK 500 & 1000 & 2000 & 5000					OFF					
★	Accept LAK 10000 & 20000 & 50000 & 100000						ON				
	Reject LAK 10000 & 20000 & 50000 & 100000						OFF				
★	Enable Output Sensor Detect							ON			
	Disable Output Sensor Detect							OFF			
★	Pulse Normal High								ON		
	Pulse Normal Low								OFF		
★	Pulse Mode									ON	
	ICT10A Mode									OFF	
★	Power On Motor Plus										ON
	Power On Motor Minus										OFF

(★) Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

- (2) Pulse mode has out of service function.
- (3) Out of service: Normal High, Error Low.
- (4) Pulse speed is LO=50ms/HI=100ms
- (5) Dip switches 1 & 2 & 4 & 8 are only used for pulse mode.

Currency Assign Data

Interface Bill value	ICT10A	Pulse
BV1	LAK 500	LAK 500
BV2	LAK 1000	LAK 1000
BV3	LAK 2000	LAK 2000
BV4	LAK 5000	LAK 5000
BV5	LAK 10000	LAK 10000
BV6	LAK 20000	LAK 20000
BV7	LAK 50000	LAK 50000
BV8	LAK 100000	LAK 100000