

# NK77-LTB9(THB+LAK)

## NK77 DIP SWITCHES SETTING : (Pulse/Out of Service/ICT10A)

Supported bill THB 20, 50, 100 3bills.

LAK 1000, 2000, 5000, 10000, 20000, 50000 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / THB 10 & LAK 1000	OFF	OFF								
	2 Pulses / THB 10 & LAK 1000	OFF	ON								
	5 Pulses / THB 10 & LAK 1000	ON	OFF								
	10 Pulses / THB 10 & LAK 1000	ON	ON								
★	Enable Fish Stop			ON							
	Disable Fish Stop			OFF							
★	Inhibit level Active Low				ON						
	Inhibit level Active High				OFF						
★	Accept THB 20 & 50 & 100					ON					
	Reject THB 20 & 50 & 100					OFF					
★	Accept LAK 1000 & 2000 & 5000 & 10000 & 20000 & 50000						ON				
	Reject LAK 1000 & 2000 & 5000 & 10000 & 20000 & 50000						OFF				
	Enable Output Sensor Detect							ON			
★	Disable Output Sensor Detect							OFF			
★	Pulse Normal High								ON		
	Pulse Normal Low								OFF		
★	Pulse Mode									ON	
	ICT10A Mode									OFF	
★	Power On Motor Plus										ON
	Power On Motor Minus										OFF

(★) Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Pulse mode has out of service function.

(3) Out of service: Normal High, Error Low.

(4) Pulse speed is LO=50ms/HI=100ms

(5) Dip switches 1 & 2 & 4 & 8 are only used for pulse mode.

### Currency Assign Data

Interface Bill value	ICT10A	Pulse
BV1	THB 20	THB 20
BV2	THB 50	THB 50
BV3	THB 100	THB 100
BV4	LAK 1000	LAK 1000
BV5	LAK 2000	LAK 2000
BV6	LAK 5000	LAK 5000
BV7	LAK 10000	LAK 10000
BV8	LAK 20000	LAK 20000
BV9	LAK 50000	LAK 50000