

NK77-MMK6

NK77/P2/P5 DIP SWITCHES SETTING : (Pulse/ICT104U)

Supported bill MMK 100, 200, 500, 1000, 5000, 10000 6 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / MMK 100	OFF	OFF								
	2 Pulses / MMK 100	OFF	ON								
	5 Pulses / MMK 100	ON	OFF								
	10 Pulses / MMK 100	ON	ON								
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>			ON							
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>			OFF							
★	Inhibit level Active Low				ON						
	Inhibit level Active High				OFF						
★	Accept MMK 100 & 200 & 500					ON					
	Reject MMK 100 & 200 & 500					OFF					
★	Accept MMK 1000 & 5000 & 10000						ON				
	Reject MMK 1000 & 5000 & 10000						OFF				
★	High Security							ON			
	High Acceptance (Note.2)							OFF			
★	Pulse Normal High								ON		
	Pulse Normal Low								OFF		
★	Pulse Mode									ON	
	ICT104U Mode									OFF	
★	Reserved										ON
	Reserved										OFF

(★) Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch

(2) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	MMK 100	MMK 100
BV2	MMK 200	MMK 200
BV3	MMK 500	MMK 500
BV4	MMK 1000	MMK 1000
BV5	MMK 5000	MMK 5000
BV6	MMK 10000	MMK 10000