

NK77F-KUR11(KHR8+USD3)

NK77F DIP SWITCHES SETTING : (ICT10A)

Supported bill KHR 500, 1000, 2000, 5000, 10000, 20000, 50000, 100000 8bills.
 USD 1, 5, 10 3bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Accept KHR 500 & 1000 & 2000	ON									
	Reject KHR 500 & 1000 & 2000	OFF									
★	Accept KHR 5000 & 10000		ON								
	Reject KHR 5000 & 10000		OFF								
★	Accept KHR 20000			ON							
	Reject KHR 20000			OFF							
★	Accept KHR 50000				ON						
	Reject KHR 50000				OFF						
★	Accept KHR 100000					ON					
	Reject KHR 100000					OFF					
★	Accept USD 1 & 5						ON				
	Reject USD 1 & 5						OFF				
★	Accept USD 10							ON			
	Reject USD 10							OFF			
★	Enable Fish Stop								ON		
	Disable Fish Stop								OFF		
	Enable Output Sensor Detect									ON	
★	Disable Output Sensor Detect									OFF	
★	Power On Motor Plus										ON
	Power On Motor Minus										OFF

(★) Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

NK77F-KUR11(ICT10A)

Currency Assign Data

Interface Bill value	ICT10A	
BV1	KHR	500
BV2	KHR	1000
BV3	KHR	2000
BV4	KHR	5000
BV5	KHR	10000
BV6	KHR	20000
BV7	KHR	50000
BV8	KHR	100000
BV9	USD	1
BV10	USD	5
BV11	USD	10