

S7A II-CAD5 Option Switch Settings (Pulse/MDB/ICT104U/Parallel A3)

Supported bill CAD 5, 10, 20, 50, 100 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject CAD 5 & 10	ON											
★	Accept CAD 5 & 10	OFF											
★	Reject CAD 20		ON										
★	Accept CAD 20		OFF										
★	Reject CAD 50			ON									
★	Accept CAD 50			OFF									
★	Reject CAD 100				ON								
★	Accept CAD 100				OFF								
★	Enable, if fishing, BA doesn't work any more					ON							
★	Disable, BA works normally					OFF							
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★	Harness Disable							ON					
★	Harness Enable							OFF					
★	Other Interface	Test Mode (No Communication)							ON				
★		Operation Mode							OFF				
★	Pulse Mode	Inhibit Active HIGH (Test)							ON				
★		Inhibit Active LOW							OFF				
★	ENABLE IrDA Download								ON				
★	Reserved								OFF				
★	ENABLE INHIBIT-Sleep Only									ON			
★	5 second Timeout Only									OFF			
	NORMAL										OFF	OFF	
	MODE1										OFF	ON	
	MODE2										ON	OFF	
★	MODE1+2										ON	ON	

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note:

NORMAL: No sleep function

MODE 1: Bill-acceptor wakes up VMC with banknote only (special cable required)

MODE 2: VMC wakes up bill-acceptor

MODE 1+2: Bill-acceptor wakes up with banknote or by VMC

S7A II-CAD5(Pulse/MDB/ICT104U/Parallel A3)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / CAD 5	(Note3)		OFF	OFF
	2 pulses / CAD 5	(Note3)		OFF	ON
	4 pulses / CAD 5	(Note3)		ON	OFF
	20 pulses / CAD 5	(Note3)		ON	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
★	ICT104U			OFF	ON
	Reserved			ON	ON
	Parallel A3			ON	OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB			OFF	OFF
	ICT104U			OFF	ON
	Reserved			ON	ON
	Parallel A3			ON	OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(Parallel A3)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
	ICT104U			OFF	ON
	Reserved			ON	ON
★	Parallel A3			ON	OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	Parallel A3
BV1	CAD 5	CAD 5	CAD 5	CAD 5
BV2	CAD 10	CAD 10	CAD 10	CAD 10
BV3	CAD 20	CAD 20	CAD 20	CAD 20
BV4	CAD 50	CAD 50	CAD 50	CAD 50
BV5	CAD 100	CAD 100	CAD 100	