

57A II-CHF6 Option Switch Settings (Pulse/MDB/ICT104U/Parallel A3)

Supported bill **CHF 10, 20, 50 3bills.**
EUR 5, 10, 20 3bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject Fr 10 & € 5	ON											
★ Accept Fr 10 & € 5	OFF											
★ Reject Fr 20 & € 10		ON										
★ Accept Fr 20 & € 10		OFF										
★ Reject Fr 50 & € 20			ON									
★ Accept Fr 50 & € 20			OFF									
★ Reject EUR				ON								
★ Accept CHF & EUR				OFF								
Enable, if fishing, BA doesn't work any more					ON							
★ Disable, BA works normally					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Stack Banknote when Power-up							ON					
★ Reject Banknote when Power-up							OFF					
★ Other Interface	Test Mode (No Communication)							ON				
	Operation Mode							OFF				
★ Pulse Mode	Inhibit Active HIGH (Test)							ON				
	Inhibit Active LOW							OFF				
★ ENABLE IrDA Download								ON				
★ Reserved									OFF			
★ ENABLE INHIBIT-Sleep Only										ON		
★ 5 second Timeout Only											OFF	
NORMAL	(Note2)										OFF	OFF
MODE1	(Note2)										OFF	ON
MODE2	(Note2)										ON	OFF
★ MODE1+2	(Note2)										ON	ON

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note: 1.1 CHF = 1 EUR

2. NORMAL : No sleep function

MODE 1 : Bill-acceptor wakes up VMC with banknote only (special cable required)

MODE 2 : VMC wakes up bill-acceptor

MODE 1+2: Bill-acceptor wakes up with banknote or by VMC

Appendix

57A II-CHF6(Pulse/MDB/ICT104U/Parallel A3)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
Other Mode		OFF		
★ 1 pulse / CHF 1			OFF	OFF
5 pulses / CHF 1			OFF	ON
10 pulses / CHF 1			ON	OFF
25 pulses / CHF 1			ON	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
★ Pulse Mode		ON		
Other Mode		OFF		
★ MDB			OFF	OFF
★ ICT104U			OFF	ON
Reserved			ON	ON
Parallel A3			ON	OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
Other Mode		OFF		
★ MDB			OFF	OFF
ICT104U			OFF	ON
Reserved			ON	ON
Parallel A3			ON	OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(Parallel A3)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
Other Mode		OFF		
★ MDB			OFF	OFF
ICT104U			OFF	ON
Reserved			ON	ON
★ Parallel A3			ON	OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	Parallel A3
BV1	Fr 10	Fr 10	Fr 10	Fr 10
BV2	Fr 20	Fr 20	Fr 20	Fr 20
BV3	Fr 50	Fr 50	Fr 50	Fr 50
BV4	€ 5	€ 5	€ 5	€ 5
BV5	€ 10	€ 10	€ 10	
BV6	€ 20	€ 20	€ 20	