

S7A II-ROL3 Option Switch Settings (Pulse/MDB/ICT/Parallel A3)

Supported bill ROL 1, 5, 10 3bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject ROL 1	ON											
★	Accept ROL 1	OFF											
★	Reject ROL 5		ON										
★	Accept ROL 5		OFF										
★	Reject ROL 10			ON									
★	Accept ROL 10			OFF									
★	Reserved				ON								
★	Reserved				OFF								
★	Enable, if fishing, BA doesn't work any more					ON							
★	Disable, BA works normally					OFF							
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★	Stack Banknote when Power-up							ON					
★	Reject Banknote when Power-up							OFF					
★	Other Interface	Test Mode (No Communication)							ON				
★		Operation Mode							OFF				
★	Pulse Mode	Inhibit Active HIGH (Test)							ON				
★		Inhibit Active LOW							OFF				
★	ENABLE IrDA Download								ON				
★	Reserved								OFF				
★	ENABLE INHIBIT-Sleep only									ON			
★	5 second Timeout only									OFF			
★	Normal (Note.2)										OFF	OFF	
★	Mode 1 (Note.3)										OFF	ON	
★	Mode 2 (Note.4)										ON	OFF	
★	Mode 1 + 2 (Note.5)										ON	ON	

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

2. Normal : No sleep function.

3. Mode 1 : Bill-acceptor wakes up VMC with banknote only (special cable required).

4. Mode 2 : VMC wakes up bill-acceptor.

5. Mode 1+2 : Bill-acceptor wakes up with banknote or by VMC.

S7A II-ROL3(Pulse/MDB/ICT/Parallel A3)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / ROL 1			OFF	OFF
	5 pulses / ROL 1			OFF	ON
	10 pulses / ROL 1			ON	OFF
	25 pulses / ROL 1			ON	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(Other)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB			OFF	OFF
	ICT			OFF	ON
	Reserved			ON	ON
	Parallel A3			ON	OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT	Parallel A3
BV1	ROL 1	ROL 1	ROL 1	ROL 1
BV2	ROL 5	ROL 5	ROL 5	ROL 5
BV3	ROL 10	ROL 10	ROL 10	ROL 10