

# S7ER-INR2 Option Switch Settings: (ICT)

Supported bill Rs 10, 20

2bills.

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
★ Reject Rs 10	ON															
★ Accept Rs 10	OFF															
★ Reject Rs 20		ON														
★ Accept Rs 20		OFF														
★ Reserved			ON													
★ Reserved			OFF													
★ Reserved				ON												
★ Reserved				OFF												
★ Reserved					ON											
★ Reserved					OFF											
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON										
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF										
★ Stack Banknote when Power-up							ON									
★ Reject Banknote when Power-up							OFF									
★ Test Mode								ON								
★ Reserved								OFF								
★ Pulse Speed	100ms on / 100ms off						ON									
	50ms on / 50ms off						OFF									
★ ENABLE INHIBIT-Sleep only							ON									
★ 5 second Timeout only							OFF									
★ Normal									OFF	OFF						
★ Mode 1									OFF	ON						
★ Mode 2									ON	OFF						
★ Mode 1 + 2									ON	ON						
★ Reserved											ON					
★ Reserved											OFF					
★ Pulse Mode													ON			
★ ICT Mode													OFF			
★ Reserved															OFF	OFF
★ Reserved															OFF	ON
★ Reserved															ON	OFF
★ Reserved															ON	ON

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

2. Normal : No sleep function.

3. Mode 1 : Bill-acceptor wakes up VMC with banknote only (special cable required).

4. Mode 2 : VMC wakes up bill-acceptor.

5. Mode 1+2 : Bill-acceptor wakes up with banknote or by VMC.