

MMK4

L70/P5 DIP SWITCHES SETTING : 1(ICT/Pulse)

Supported bill K 500, 1000, 5000, 10000 4 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / K 500	OFF	OFF	OFF							
	2 Pulse / K 500	OFF	OFF	ON							
	3 Pulse / K 500	OFF	ON	OFF							
	4 Pulse / K 500	OFF	ON	ON							
	5 Pulse / K 500	ON	OFF	OFF							
	10 Pulse / K 500	ON	OFF	ON							
	20 Pulse / K 500	ON	ON	OFF							
	100 Pulse / K 500	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept K 500					ON					
	Reject K 500					OFF					
★	Accept K 1000						ON				
	Reject K 1000						OFF				
★	Accept K 5000							ON			
	Reject K 5000							OFF			
★	Accept K 10000								ON		
	Reject K 10000								OFF		
★	Reserved									ON	
	Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT Protocol Mode (ICT106U)		OFF		
	Reserved			ON	
				OFF	
					ON
★					OFF

Currency Assign Data

Interface Bill value	Pulse	ICT106U
BV1	K 500	K 500
BV2	K 1000	K 1000
BV3	K 5000	K 5000
BV4	K 10000	K 10000