

L70/L70F-MXN5

L70/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill N\$ 20, 50, 100, 200, 500 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / N\$ 10	OFF	OFF	OFF							
	2 Pulse / N\$ 10	OFF	OFF	ON							
	3 Pulse / N\$ 10	OFF	ON	OFF							
	4 Pulse / N\$ 10	OFF	ON	ON							
	5 Pulse / N\$ 10	ON	OFF	OFF							
	10 Pulse / N\$ 10	ON	OFF	ON							
	20 Pulse / N\$ 10	ON	ON	OFF							
	100 Pulse / N\$ 10	ON	ON	ON							
★	Fast output Pulse Lo= 50ms Hi=100ms				ON						
	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
★	Inhibit level Active Low					ON					
	Inhibit level Active High					OFF					
★	Accept N\$ 20						ON				
	Reject N\$ 20						OFF				
★	Accept N\$ 50							ON			
	Reject N\$ 50							OFF			
★	Accept N\$ 100								ON		
	Reject N\$ 100								OFF		
★	Accept N\$ 200									ON	
	Reject N\$ 200									OFF	
★	Accept N\$ 500										ON
	Reject N\$ 500										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70/L70F-MXN5/P5(Pulse/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104U Interface		OFF		
★	Reserved			ON	
				OFF	
★					ON
★					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON		
★	ICT104U Interface		OFF		
★	Reserved			ON	
				OFF	
★					ON
★					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	N\$ 20	N\$ 20
BV2	N\$ 50	N\$ 50
BV3	N\$ 100	N\$ 100
BV4	N\$ 200	N\$ 200
BV5	N\$ 500	N\$ 500