

L70-NAD9(NAD6+ZAR3)

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill NAD 10, 20, 30, 50, 100, 200 6 bills.
ZAR 50, 100, 200 3 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / \$ 10	OFF	OFF	OFF							
	2 Pulse / \$ 10	OFF	OFF	ON							
	3 Pulse / \$ 10	OFF	ON	OFF							
	4 Pulse / \$ 10	OFF	ON	ON							
	5 Pulse / \$ 10	ON	OFF	OFF							
	10 Pulse / \$ 10	ON	OFF	ON							
	20 Pulse / \$ 10	ON	ON	OFF							
	100 Pulse / \$ 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept \$ 10 & \$ 20 & \$ 30				ON						
	Reject \$ 10 & \$ 20 & \$ 30				OFF						
★	Accept \$ 50 & R 50				ON						
	Reject \$ 50 & R 50				OFF						
★	Accept \$100 & R100				ON						
	Reject \$100 & R100				OFF						
★	Accept \$200 & R200				ON						
	Reject \$200 & R200				OFF						
	Accept NAD ONLY				ON						
★	Accept NAD+ZAR				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70-NAD9(NAD6+ZAR3)(Pulse/ICT104U)

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT Mode		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	\$ 10	\$ 10
BV2	\$ 20	\$ 20
BV3	\$ 30	\$ 30
BV4	\$ 50	\$ 50
BV5	\$ 100	\$ 100
BV6	\$ 200	\$ 200
BV7	R 50	R 50
BV8	R 100	R 100
BV9	R 200	R 200