

L70-NAD6

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill \$ 10, 20, 30, 50, 100, 200 6 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / \$ 10	OFF	OFF	OFF							
2 Pulse / \$ 10	OFF	OFF	ON							
3 Pulse / \$ 10	OFF	ON	OFF							
4 Pulse / \$ 10	OFF	ON	ON							
5 Pulse / \$ 10	ON	OFF	OFF							
10 Pulse / \$ 10	ON	OFF	ON							
20 Pulse / \$ 10	ON	ON	OFF							
100 Pulse / \$ 10	ON	ON	ON							
★ Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
★ Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept \$ 10						ON				
Reject \$ 10						OFF				
★ Accept \$ 20 & \$ 30							ON			
Reject \$ 20 & \$ 30							OFF			
★ Accept \$ 50								ON		
Reject \$ 50								OFF		
★ Accept \$ 100									ON	
Reject \$ 100									OFF	
★ Accept \$ 200										ON
Reject \$ 200										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Credit - Pulse Normal High	ON			
Credit - Pulse Normal Low	OFF			
★ Pulse Mode		ON		
ICT104U Mode		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

Currency Assign Data

Interface Bill value	Pulse	ICT
BV1	10	10
BV2	20	20
BV3	30	30
BV4	50	50
BV5	100	100
BV6	200	200