

SAR4

L70/P5 DIP SWITCHES SETTING : 1(ICT/Pulse)

Supported bill 1, 5, 10, 20 س.ر 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / 1 س.ر	OFF	OFF	OFF							
	2 Pulse / 1 س.ر	OFF	OFF	ON							
	3 Pulse / 1 س.ر	OFF	ON	OFF							
	4 Pulse / 1 س.ر	OFF	ON	ON							
	5 Pulse / 1 س.ر	ON	OFF	OFF							
	10 Pulse / 1 س.ر	ON	OFF	ON							
	20 Pulse / 1 س.ر	ON	ON	OFF							
	100 Pulse / 1 س.ر	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept 1 س.ر					ON					
	Reject 1 س.ر					OFF					
★	Accept 5 س.ر						ON				
	Reject 5 س.ر						OFF				
★	Accept 10 س.ر							ON			
	Reject 10 س.ر							OFF			
★	Accept 20 س.ر								ON		
	Reject 20 س.ر								OFF		
★	Reserve										ON
	Reserve										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT Mode		OFF		
	Reserved			ON	
				OFF	
					ON
					OFF

Currency Assign Data

Interface Bill value	Pulse	ICT
BV1	1	1
BV2	5	5
BV3	10	10
BV4	20	20
BV5	0	0
BV6	0	0
BV7	0	0