

L70-TWD4

L70 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccNet)

Supported bill TWD 100, 200, 500, 1000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / TWD 100	OFF	OFF	OFF							
	2 Pulse / TWD 100	OFF	OFF	ON							
	3 Pulse / TWD 100	OFF	ON	OFF							
	4 Pulse / TWD 100	OFF	ON	ON							
	5 Pulse / TWD 100	ON	OFF	OFF							
	10 Pulse / TWD 100	ON	OFF	ON							
	20 Pulse / TWD 100	ON	ON	OFF							
	100 Pulse / TWD 100	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept TWD 100						ON				
	Reject TWD 100						OFF				
★	Accept TWD 200							ON			
	Reject TWD 200							OFF			
★	Accept TWD 500								ON		
	Reject TWD 500								OFF		
★	Accept TWD 1000									ON	
	Reject TWD 1000									OFF	
★	Reserved										ON
	Reserved										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only for Pulse model.

Currency Assign Data

Interface Bill value	ICT104U	Pulse	ccNet
BV1	100	100	100
BV2	200	200	200
BV3	500	500	500
BV4	1000	1000	1000

L70-TWD4(Pulse/ICT104U/ccNet)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Protocol Mode		ON	ON	
	ccNet Mode		OFF	OFF	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON	OFF	
★	ICT104U Protocol Mode		ON	ON	
	ccNet Mode		OFF	OFF	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccNet)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	9600 baud Rate	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Protocol Mode		ON	ON	
★	ccNet Mode		OFF	OFF	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting