

L70-ZAR5

L70/P5 DIP SWITCHES SETTING : 1(ICT/Pulse)

Supported bill ZAR 10, 20, 50, 100, 200 5 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / ZAR 10	OFF	OFF	OFF							
	2 Pulse / ZAR 10	OFF	OFF	ON							
	3 Pulse / ZAR 10	OFF	ON	OFF							
	4 Pulse / ZAR 10	OFF	ON	ON							
	5 Pulse / ZAR 10	ON	OFF	OFF							
	10 Pulse / ZAR 10	ON	OFF	ON							
	20 Pulse / ZAR 10	ON	ON	OFF							
	100 Pulse / ZAR 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept ZAR 10						ON				
	Reject ZAR 10						OFF				
★	Accept ZAR 20							ON			
	Reject ZAR 20							OFF			
★	Accept ZAR 50								ON		
	Reject ZAR 50								OFF		
★	Accept ZAR 100									ON	
	Reject ZAR 100									OFF	
★	Accept ZAR 200										ON
	Reject ZAR 200										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70-ZAR5(ICT/Pulse)

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT Mode		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	10	10
BV2	20	20
BV3	50	50
BV4	100	100
BV5	200	200