

## L70+/L70F-JMD6

### L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill JMD 50, 100, 500, 1000, 2000, 5000 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / JMD 50 & 100 (Note.3)	OFF	OFF	OFF							
2 Pulses / JMD 50 & 100 (Note.3)	OFF	OFF	ON							
3 Pulses / JMD 50 & 100 (Note.3)	OFF	ON	OFF							
4 Pulses / JMD 50 & 100 (Note.3)	OFF	ON	ON							
5 Pulses / JMD 50 & 100 (Note.3)	ON	OFF	OFF							
10 Pulses / JMD 50 & 100 (Note.3)	ON	OFF	ON							
20 Pulses / JMD 50 & 100 (Note.3)	ON	ON	OFF							
100 Pulses / JMD 50 & 100 (Note.3)	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi= 50ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept JMD 50						ON				
Reject JMD 50						OFF				
★ Accept JMD 100 & 500							ON			
Reject JMD 100 & 500							OFF			
★ Accept JMD 1000								ON		
Reject JMD 1000								OFF		
★ Accept JMD 2000									ON	
Reject JMD 2000									OFF	
★ Accept JMD 5000										ON
Reject JMD 5000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) When DIP6 ON : 1 pulse/ JMD 50

When DIP6 OFF: 1 pulse/ JMD 100

## L70+/L70F-JMD6/P5(Pulse/ICT104U)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
ICT104U Interface Mode		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
★ ICT104U Interface Mode		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	Pulse		ICT104U
	When DIP6 ON	When DIP6 OFF	
BV1	JMD 50	JMD 100	JMD 50
BV2	JMD 100	JMD 500	JMD 100
BV3	JMD 500	JMD 1000	JMD 500
BV4	JMD 1000	JMD 5000	JMD 1000
BV5	JMD 5000	JMD 2000	JMD 5000
BV6	JMD 2000		JMD 2000