

L70+/L70F-MMK4

L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill MMK 500, 1000, 5000, 10000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / MMK 500	OFF	OFF	OFF							
	2 Pulse / MMK 500	OFF	OFF	ON							
	3 Pulse / MMK 500	OFF	ON	OFF							
	4 Pulse / MMK 500	OFF	ON	ON							
	5 Pulse / MMK 500	ON	OFF	OFF							
	10 Pulse / MMK 500	ON	OFF	ON							
	20 Pulse / MMK 500	ON	ON	OFF							
	100 Pulse / MMK 500	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept MMK 500					ON					
	Reject MMK 500					OFF					
★	Accept MMK 1000						ON				
	Reject MMK 1000						OFF				
★	Accept MMK 5000							ON			
	Reject MMK 5000							OFF			
★	Accept MMK 10000								ON		
	Reject MMK 10000								OFF		
★	High Security									ON	
	High Acceptance (Note.3)										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

L70+/L70F-MMK4/P5(Pulse/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104U Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	ICT104U Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	MMK 500	MMK 500
BV2	MMK 1000	MMK 1000
BV3	MMK 5000	MMK 5000
BV4	MMK 10000	MMK 10000