

P70-CLP5

P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill Ch\$ 1000, 2000, 5000, 10000, 20000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10		
★	1 Pulse / Ch\$ 1000	OFF	OFF	OFF									
	2 Pulse / Ch\$ 1000	OFF	OFF	ON									
	3 Pulse / Ch\$ 1000	OFF	ON	OFF									
	4 Pulse / Ch\$ 1000	OFF	ON	ON									
	5 Pulse / Ch\$ 1000	ON	OFF	OFF									
	10 Pulse / Ch\$ 1000	ON	OFF	ON									
	20 Pulse / Ch\$ 1000	ON	ON	OFF									
	100 Pulse / Ch\$ 1000	ON	ON	ON									
	Fast output Pulse Lo= 50ms Hi=100ms				ON								
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF								
	Inhibit level Active Low					ON							
★	Inhibit level Active High					OFF							
★	Accept Ch\$ 1000						ON						
	Reject Ch\$ 1000						OFF						
★	Accept Ch\$ 2000							ON					
	Reject Ch\$ 2000							OFF					
★	Accept Ch\$ 5000								ON				
	Reject Ch\$ 5000								OFF				
★	Accept Ch\$ 10000									ON			
	Reject Ch\$ 10000									OFF			
★	Accept Ch\$ 20000										ON		
	Reject Ch\$ 20000										OFF		

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT104U Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	1000	1000
BV2	2000	2000
BV3	5000	5000
BV4	10000	10000
BV5	20000	20000