

P70-COP5

P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill Col\$ 1000, 2000, 5000, 10000, 20000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Col\$ 1000	OFF	OFF	OFF							
	2 Pulse / Col\$ 1000	OFF	OFF	ON							
	3 Pulse / Col\$ 1000	OFF	ON	OFF							
	4 Pulse / Col\$ 1000	OFF	ON	ON							
	5 Pulse / Col\$ 1000	ON	OFF	OFF							
	10 Pulse / Col\$ 1000	ON	OFF	ON							
	20 Pulse / Col\$ 1000	ON	ON	OFF							
	100 Pulse / Col\$ 1000	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept Col\$ 1000						ON				
	Reject Col\$ 1000						OFF				
★	Accept Col\$ 2000							ON			
	Reject Col\$ 2000							OFF			
★	Accept Col\$ 5000								ON		
	Reject Col\$ 5000								OFF		
★	Accept Col\$ 10000									ON	
	Reject Col\$ 10000									OFF	
★	Accept Col\$ 20000										ON
	Reject Col\$ 20000										OFF

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT Protocol		OFF		
★	Harness Disable			ON	
	Harness Enable			OFF	
	Manufacture Default				
★	System Default				OFF

★ Manufacture setting.

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	Col\$ 1000	Col\$ 1000
BV2	Col\$ 2000	Col\$ 2000
BV3	Col\$ 5000	Col\$ 5000
BV4	Col\$ 10000	Col\$ 10000
BV5	Col\$ 20000	Col\$ 20000