

P70-MXP5

P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill M\$ 20, 50, 100, 200, 500 5 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / M\$ 10	OFF	OFF	OFF							
	2 Pulse / M\$ 10	OFF	OFF	ON							
	3 Pulse / M\$ 10	OFF	ON	OFF							
	4 Pulse / M\$ 10	OFF	ON	ON							
	5 Pulse / M\$ 10	ON	OFF	OFF							
	10 Pulse / M\$ 10	ON	OFF	ON							
	20 Pulse / M\$ 10	ON	ON	OFF							
	100 Pulse / M\$ 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept M\$ 20				ON						
	Reject M\$ 20				OFF						
★	Accept M\$ 50				ON						
	Reject M\$ 50				OFF						
★	Accept M\$ 100				ON						
	Reject M\$ 100				OFF						
★	Accept M\$ 200				ON						
	Reject M\$ 200				OFF						
★	Accept M\$ 500				ON						
	Reject M\$ 500				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

Currency Assign Data

Interface Bill value	Pulse	ICT
BV1	M\$ 20	M\$ 20
BV2	M\$ 50	M\$ 50
BV3	M\$ 100	M\$ 100
BV4	M\$ 200	M\$ 200
BV5	M\$ 500	M\$ 500