

BYR6

P77/P5 DIP SWITCHES SETTING : 1(Pulse/RS232 A0)

Supported bill BYN 1000, 5000, 10000, 20000,
50000, 100000 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / BYR 1000	OFF	OFF	OFF							
	2 Pulses / BYR 1000	OFF	OFF	ON							
	3 Pulses / BYR 1000	OFF	ON	OFF							
	4 Pulses / BYR 1000	OFF	ON	ON							
	5 Pulses / BYR 1000	ON	OFF	OFF							
	10 Pulses / BYR 1000	ON	OFF	ON							
	20 Pulses / BYR 1000	ON	ON	OFF							
	100 Pulses / BYR 1000	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept Ruble BYR 1000 & 5000				ON						
	Reject Ruble BYR 1000 & 5000				OFF						
★	Accept Ruble BYR 10000 & 20000				ON						
	Reject Ruble BYR 10000 & 20000				OFF						
★	Accept Ruble BYR 50000				ON						
	Reject Ruble BYR 50000				OFF						
★	Accept Ruble BYR100000				ON						
	Reject Ruble BYR100000				OFF						
	Reserved										ON
★	Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

P77-BYR6(Pulse/RS232 A0)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	RS232 A0 Mode		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	RS232 A0 Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

RS232 A0 INFORMATION

Bill Type Data	
Code	Denomination
1	Reserved
2	Reserved
3	BYR 1000
4	Reserved
5	BYR 5000
6	BYR 10000
7	BYR 20000
8	BYR 50000
9	BYR100000