



BYR7

P77/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill Ruble 100, 500, 1000, 5000, 10000, 20000, 50000
7 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Ruble 100	OFF	OFF	OFF							
2 Pulse / Ruble 100	OFF	OFF	ON							
3 Pulse / Ruble 100	OFF	ON	OFF							
4 Pulse / Ruble 100	OFF	ON	ON							
5 Pulse / Ruble 100	ON	OFF	OFF							
10 Pulse / Ruble 100	ON	OFF	ON							
20 Pulse / Ruble 100	ON	ON	OFF							
100 Pulse / Ruble 100	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low				ON						
★ Inhibit level Active High				OFF						
★ Accept Ruble 100 & 500				ON						
★ Reject Ruble 100 & 500				OFF						
★ Accept Ruble 1000				ON						
★ Reject Ruble 1000				OFF						
★ Accept Ruble 5000				ON						
★ Reject Ruble 5000				OFF						
★ Accept Ruble 10000				ON						
★ Reject Ruble 10000				OFF						
★ Accept Ruble 20000 & 50000				ON						
★ Reject Ruble 20000 & 50000				OFF						

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
ICT Protocol		OFF		
★ Harness Disable			ON	
★ Harness Enable			OFF	
★ Ignore Sensor Problem(Note 1)				ON
★ Acknowledge Sensor Problem (Note 2)				OFF

★ Manufacture setting

Note : (1) Sensor 6 problem occurred ==>> BA will be still in working order.

(The face LED will be flashing in short red about 2 seconds everytime you restart BA.)

(2) BA will stop to work when it acknowledges Sensor 6 problem occurred.

(The face LED will be flashing in red.)