



**BYR7**

**P77/P5 DIP SWITCHES SETTING : 1(Pulse/Parallel)**

**Supported bill Ruble 500, 1000, 5000, 10000, 20000,  
50000, 100000 7bills.**

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / Ruble 500	OFF	OFF	OFF								
	2 Pulse / Ruble 500	OFF	OFF	ON								
	3 Pulse / Ruble 500	OFF	ON	OFF								
	4 Pulse / Ruble 500	OFF	ON	ON								
	5 Pulse / Ruble 500	ON	OFF	OFF								
	10 Pulse / Ruble 500	ON	OFF	ON								
	20 Pulse / Ruble 500	ON	ON	OFF								
	100 Pulse / Ruble 500	ON	ON	ON								
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>											ON
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>											OFF
	Inhibit level Active Low				ON							
★	Inhibit level Active High				OFF							
★	Accept Ruble 500 & 1000						ON					
	Reject Ruble 500 & 1000						OFF					
★	Accept Ruble 5000 & 10000							ON				
	Reject Ruble 5000 & 10000							OFF				
★	Accept Ruble 20000								ON			
	Reject Ruble 20000								OFF			
★	Accept Ruble 50000									ON		
	Reject Ruble 50000									OFF		
★	Accept Ruble 100000										ON	
	Reject Ruble 100000										OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## ***P77-BYR7/P5(Pulse/Parallel)***

### **DIP SWITCHES SETTING : 2(Pulse)**

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	Parallel Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

### **DIP SWITCHES SETTING : 2(Parallel)**

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Protocol		ON		
★	Parallel Protocol		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting