

P77-CZK6

P77/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill CZK 100, 200, 500, 1000, 2000, 5000 6 bills.

With stacker : 100, 200, 500, 1000, 2000

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / CZK 50	OFF	OFF	OFF							
	2 Pulse / CZK 50	OFF	OFF	ON							
	3 Pulse / CZK 50	OFF	ON	OFF							
	4 Pulse / CZK 50	OFF	ON	ON							
	5 Pulse / CZK 50	ON	OFF	OFF							
	10 Pulse / CZK 50	ON	OFF	ON							
	20 Pulse / CZK 50	ON	ON	OFF							
	100 Pulse / CZK 50	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept CZK 100					ON					
★	Reject CZK 100					OFF					
★	Accept CZK 200 & 500						ON				
	Reject CZK 200 & 500						OFF				
★	Accept CZK 1000							ON			
	Reject CZK 1000							OFF			
★	Accept CZK 2000								ON		
	Reject CZK 2000								OFF		
★	Accept CZK 5000									ON	
	Reject CZK 5000									OFF	

★ Manufacture setting
 Note: (1) Please reset the bill acceptor after set the dip switch.
 (2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2 Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT104U Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Disable Continuous Accept				ON
★	Enable Continuous Accept				OFF

Interface Bill value	Pulse	ICT104U
BV1		
BV2	CZK 100	CZK 100
BV3	CZK 200	CZK 200
BV4	CZK 500	CZK 500
BV5	CZK 1000	CZK 1000
BV6	CZK 2000	CZK 2000
BV7	CZK 5000	CZK 5000

★ Manufacture setting