

## P77-EUR6

### P77/P5 DIP SWITCHES SETTING : 1(Pulse/Parallel A3)

Supported bill € 5, 10, 20, 50, 100, 200 6 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / € 5	OFF	OFF	OFF							
	2 Pulses / € 5	OFF	OFF	ON							
	3 Pulses / € 5	OFF	ON	OFF							
	4 Pulses / € 5	OFF	ON	ON							
	5 Pulses / € 5	ON	OFF	OFF							
	10 Pulses / € 5	ON	OFF	ON							
	20 Pulses / € 5	ON	ON	OFF							
	100 Pulses / € 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept € 5					ON					
	Reject € 5					OFF					
★	Accept € 10 & 20					ON					
	Reject € 10 & 20					OFF					
★	Accept € 50					ON					
	Reject € 50					OFF					
	Accept € 100(2019) & 200(2019)					ON					
★	Reject € 100(2019) & 200(2019)					OFF					
★	Accept Normal					ON					
	Reject € 5 (2002) & 10(2002)					OFF					

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## P77-EUR6/P5(Pulse/Parallel A3)

### DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	Parallel A3 Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(Parallel A3)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Protocol		ON		
★	Parallel A3 Protocol		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

### Currency Assign Data

Interface Bill value	Parallel A3	Pulse
BV1	€ 5	€ 5
BV2	€ 10	€ 10
BV3	€ 20	€ 20
BV4	€ 50	€ 50
BV5		€ 100
BV6		€ 200