

P77-GNP2

P77/P5 DIP SWITCHES SETTING : 1(Pulse/ccTalk)

Supported bill
【England】

Bank of England
【Northern Ireland】

Bank of Ireland

Ulster Bank

Northern Bank

First trust Bank

5, 10 2bills.

5, 10 2bills.

5, 10 2bills.

10 1bills.

10 1bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / £ 5	OFF	OFF	OFF							
	2 Pulse / £ 5	OFF	OFF	ON							
	3 Pulse / £ 5	OFF	ON	OFF							
	4 Pulse / £ 5	OFF	ON	ON							
	5 Pulse / £ 5	ON	OFF	OFF							
	10 Pulse / £ 5	ON	OFF	ON							
	20 Pulse / £ 5	ON	ON	OFF							
	100 Pulse / £ 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept England & Northern Ireland 5				ON						
	Reject England & Northern Ireland 5				OFF						
★	Accept England & Northern Ireland 10				ON						
	Reject England & Northern Ireland 10				OFF						
★	Accept England new polymer £5(2015)				ON						
	Reject England new polymer £5(2015)				OFF						
★	Reserved				ON						
	Reserved				OFF						
★	Reserved				ON						
	Reserved				OFF						

(★) Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

P77-GNP2/P5(Pulse/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ccTalk Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Reserved				ON
★	Reserved				OFF

(★) Manufacture setting

DIP SWITCHES SETTING : 3(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
★	Encryption MODE	ON			
	Decrypt MODE	OFF			
	Pulse Protocol		ON		
★	ccTalk Protocol		OFF		
	ccTalk Parameters Reset			ON	
★	Keep ccTalk Parameters			OFF	
	Reserved				ON
★	Reserved				OFF

(★) Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) ccTalk Parameters Reset

Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

*This has to be done after finished calibration process.

Currency Assign Data

Interface Bill value	Pulse	ccTalk
BV1	GBP £ 5 (England BOE)	GBP £ 5 (England BOE)
BV2	GBP £ 10 (England BOE)	GBP £ 10 (England BOE)
BV3	GBP £ 5 (Northern Ireland BI)	GBP £ 5 (Northern Ireland BI)
BV4	GBP £ 5 (Northern Ireland NB)	GBP £ 5 (Northern Ireland NB)
BV5	GBP £ 5 (Northern Ireland UB)	GBP £ 5 (Northern Ireland UB)
BV6	GBP £ 10 (Northern Ireland FT)	GBP £ 10 (Northern Ireland FT)
BV7	GBP £ 10 (Northern Ireland BI)	GBP £ 10 (Northern Ireland BI)
BV8	GBP £ 10 (Northern Ireland NB)	GBP £ 10 (Northern Ireland NB)
BV9	GBP £ 10 (Northern Ireland UB)	GBP £ 10 (Northern Ireland UB)
BV10	GBP £ 5 (England BOE)	GBP £ 5 (England BOE)