



# INR5

## P77P5 DIP SWITCHES SETTING : 1(Pulse/ MDB)

Supported bill Rs 5, 10, 20, 50, 100

5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Rs 5	OFF	OFF	OFF							
	2 Pulse / Rs 5	OFF	OFF	ON							
	3 Pulse / Rs 5	OFF	ON	OFF							
	4 Pulse / Rs 5	OFF	ON	ON							
	5 Pulse / Rs 5	ON	OFF	OFF							
	10 Pulse / Rs 5	ON	OFF	ON							
	20 Pulse / Rs 5	ON	ON	OFF							
	100 Pulse / Rs 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept Rs 5 & 10 & 20						ON				
	Reject Rs 5 & 10 & 20						OFF				
★	Accept Rs 50							ON			
	Reject Rs 50							OFF			
★	Accept Rs 100								ON		
	Reject Rs 100								OFF		
	Reserved									ON	
★	Reserved									OFF	
	Reserved										ON
★	Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

**DIP SWITCHES SETTING : 2(Pulse)**

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	MDB Interface		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

**DIP SWITCHES SETTING : 2(MDB)**

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	MDB Interface		OFF		
	Reserved			ON	
★				OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting