

P77-KZT5

P77/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill KZT 200, 500, 1000, 2000, 5000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / KZT 100	OFF	OFF	OFF							
	2 Pulse / KZT 100	OFF	OFF	ON							
	3 Pulse / KZT 100	OFF	ON	OFF							
	4 Pulse / KZT 100	OFF	ON	ON							
	5 Pulse / KZT 100	ON	OFF	OFF							
	10 Pulse / KZT 100	ON	OFF	ON							
	20 Pulse / KZT 100	ON	ON	OFF							
	100 Pulse / KZT 100	ON	ON	ON							
★	Fast output Pulse Lo= 50ms Hi=100ms				ON						
	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
★	Inhibit level Active Low					ON					
	Inhibit level Active High					OFF					
★	Accept KZT 200						ON				
	Reject KZT 200						OFF				
★	Accept KZT 500							ON			
	Reject KZT 500							OFF			
★	Accept KZT 1000								ON		
	Reject KZT 1000								OFF		
★	Accept KZT 2000									ON	
	Reject KZT 2000									OFF	
★	Accept KZT 5000										ON
	Reject KZT 5000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT104U Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U
BV1	KZT 200	KZT 200
BV2	KZT 500	KZT 500
BV3	KZT 1000	KZT 1000
BV4	KZT 2000	KZT 2000
BV5	KZT 5000	KZT 5000