

P77-UAH9

P77/P5 DIP SWITCHES SETTING : 1(Pulse/MDB)

Supported bill H 1, 2, 5, 10, 20, 50, 100, 200, 500 9bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / H 1 & 5 (Note.3)	OFF	OFF	OFF							
2 Pulse / H 1 & 5 (Note.3)	OFF	OFF	ON							
3 Pulse / H 1 & 5 (Note.3)	OFF	ON	OFF							
4 Pulse / H 1 & 5 (Note.3)	OFF	ON	ON							
5 Pulse / H 1 & 5 (Note.3)	ON	OFF	OFF							
10 Pulse / H 1 & 5 (Note.3)	ON	OFF	ON							
20 Pulse / H 1 & 5 (Note.3)	ON	ON	OFF							
100 Pulse / H 1 & 5 (Note.3)	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept H 1 & 2 (Note.3)						ON				
★ Reject H 1 & 2 (Note.3)						OFF				
★ Accept H 5 & 10							ON			
★ Reject H 5 & 10							OFF			
★ Accept H 20 & 50								ON		
★ Reject H 20 & 50								OFF		
★ Accept H 100 & 200									ON	
★ Reject H 100 & 200									OFF	
★ Accept H 500										ON
★ Reject H 500										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Pulse Mode:

When Dip 6 is ON,One Pulse per UAH 1.

When Dip 6 is OFF,One Pulse per UAH 5.

MDB Mode:

When Dip 6 is ON,Reject UAH 500.

When Dip 6 is OFF,Accept UAH 500.

P77-UAH9/P5(Pulse/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON		
MDB Interface		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON		
★ MDB Interface		OFF		
Reserved			ON	
★ Reserved			OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse		MDB	
	When Dip 6 is ON	When Dip 6 is OFF	When Dip 6 is ON	When Dip 6 is OFF
BV1	UAH 1		UAH 1	UAH 5
BV2	UAH 2		UAH 2	UAH 10
BV3	UAH 5	UAH 5	UAH 5	UAH 20
BV4	UAH 10	UAH 10	UAH 10	UAH 50
BV5	UAH 20	UAH 20	UAH 20	UAH 100
BV6	UAH 50	UAH 50	UAH 50	UAH 200
BV7	UAH 100	UAH 100	UAH 100	UAH 500
BV8	UAH 200	UAH 200	UAH 200	
BV9	UAH 500	UAH 500		