

P85-EUR6

P85/P2/P5 DIP SWITCHES SETTING : 1(Pulse/M.D.B)

Supported bill € 5, 10, 20, 50, 100, 200 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / € 5	OFF	OFF	OFF							
2 Pulse / € 5	OFF	OFF	ON							
3 Pulse / € 5	OFF	ON	OFF							
4 Pulse / € 5	OFF	ON	ON							
5 Pulse / € 5	ON	OFF	OFF							
10 Pulse / € 5	ON	OFF	ON							
20 Pulse / € 5	ON	ON	OFF							
100 Pulse / € 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi= 100ms				ON						
★ Slow output Pulse Lo= 50ms Hi= 300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept € 5						ON				
Reject € 5						OFF				
★ Accept € 10 & 20							ON			
Reject € 10 & 20							OFF			
★ Accept € 50								ON		
Reject € 50								OFF		
★ Accept € 100 & 200									ON	
Reject € 100 & 200									OFF	
★ Accept Normal										ON
Reject € 5(2002) & 10(2002)										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.
(2) Dip switches 1 to 5 are only used for pulse protocol.

P85-EUR6/P5(Pulse/M.D.B)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON		
M.D.B Interface		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting.

DIP SWITCHES SETTING : 3(M.D.B)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON		
★ M.D.B Interface		OFF		
Reserved			ON	
★ Reserved			OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting.

Currency Assign Data

Interface Bill value	MDB	Pulse
BV1	€ 5	€ 5
BV2	€ 10	€ 10
BV3	€ 20	€ 20
BV4	€ 50	€ 50
BV5	€ 100	€ 100
BV6	€ 200	€ 200