

## P85-ROL7

### P85/P5 DIP SWITCHES SETTING : 1(ICT104U/RS232 A1)

Supported bill Lei 1, 5, 10, 50, 100, 200, 500 7bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ ★ ★ ★ ★ ★ ★ ★ Reserved	ON									
	OFF									
		ON								
		OFF								
			ON							
			OFF							
				ON						
				OFF						
Accept Lei 1					ON					
Reject Lei 1					OFF					
Accept Lei 5						ON				
Reject Lei 5						OFF				
Accept Lei 10							ON			
Reject Lei 10							OFF			
Accept Lei 50 & 100								ON		
Reject Lei 50 & 100								OFF		
Accept Lei 200 & 500										ON
Reject Lei 200 & 500										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

### DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ RS232 A1 Mode		ON		
ICT104U Mode		OFF		
★ Reserved			ON	
			OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Note : (1) Please reset the bill acceptor after set the dip switch.

### Currency Assign Data

Interface	ICT104U	RS232 A1
Bill value		
BV1	Lei 1	Lei 1
BV2	Lei 5	Lei 5
BV3	Lei 10	Lei 10
BV4	Lei 50	Lei 50
BV5	Lei 100	Lei 100
BV6	Lei 200	Lei 200
BV7	Lei 500	Lei 500