

P85-RON7

P85/P5 DIP SWITCHES SETTING : 1(Pulse/M.D.B)

Supported bill Lei 1, 5, 10, 50, 100, 200, 500 7bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Lei 1	OFF	OFF	OFF							
	2 Pulse / Lei 1	OFF	OFF	ON							
	3 Pulse / Lei 1	OFF	ON	OFF							
	4 Pulse / Lei 1	OFF	ON	ON							
	5 Pulse / Lei 1	ON	OFF	OFF							
	10 Pulse / Lei 1	ON	OFF	ON							
	20 Pulse / Lei 1	ON	ON	OFF							
	100 Pulse / Lei 1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept Lei 1					ON					
	Reject Lei 1					OFF					
★	Accept Lei 5						ON				
	Reject Lei 5						OFF				
★	Accept Lei 10							ON			
	Reject Lei 10							OFF			
★	Accept Lei 50 & 100								ON		
	Reject Lei 50 & 100								OFF		
★	Accept Lei 200 & 500									ON	
	Reject Lei 200 & 500									OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

P85-RON7/P5(Pulse/M.D.B)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	M.D.B Interface		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting.

DIP SWITCHES SETTING : 2(M.D.B)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	M.D.B Interface		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting.

Currency Assign Data

Interface Bill value	MDB		Pulse
	When Dip 6 is ON	When Dip 6 is OFF	
BV1	Lei 1	Lei 5	Lei 1
BV2	Lei 5	Lei 10	Lei 5
BV3	Lei 10	Lei 50	Lei 10
BV4	Lei 50	Lei 100	Lei 50
BV5	Lei 100	Lei 200	Lei 100
BV6	Lei 200	Lei 500	Lei 200
BV7			Lei 500