

## TRY5 (ccTalk/Parallel)

### SCA1 DIP SWITCHES SETTING : 1

Supported coin £ 0.05, 0.1, 0.25, 0.5, 1 5 coins.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Accept £ 5 New Kurus	OFF									
	Reject £ 5 New Kurus	ON									
★	Accept £ 10 New Kurus		OFF								
	Reject £ 10 New Kurus		ON								
★	Accept £ 25 New Kurus			OFF							
	Reject £ 25 New Kurus			ON							
★	Accept £ 50 New Kurus				OFF						
	Reject £ 50 New Kurus				ON						
★	Accept £ 1 New Lira					OFF					
	Reject £ 1 New Lira					ON					
★	Reserved						OFF				
	Reserved						ON				
★	Reserved							OFF			
	Reserved							ON			
★	Reserved								OFF		
	Reserved								ON		
★	Reserved										
	Reserved										
	ccTalk Protocol									OFF	
	Paralle Protocol									ON	
★	Block 0										OFF
	Block 1										ON

★ Manufacture setting

### Currency Assign Data

Channel Currency	Paralle
Channel 1 : 5 New Kurus	1
Channel 2 : 10 New Kurus	2
Channel 3 : 25 New Kurus	3
Channel 4 : 50 New Kurus	4
Channel 5 : 1 New Lira	5

### DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reserved	OFF									
	Reserved	ON									
★	Reserved		OFF								
	Reserved		ON								
★	Reserved			OFF							
	Reserved			ON							
★	Reserved				OFF						
	Reserved				ON						
★	Reserved					OFF					
	Reserved					ON					
★	Reserved						OFF				
	Reserved						ON				
★	Reserved								OFF		
	Reserved								ON		
	User define									ON	ON
★	ICT									OFF	OFF
	Mode 1									ON	OFF
	Mode 2									OFF	ON

★ Manufacture setting.  
SW9 - SW10 : ccTalk for Sorter Setup. (Top Entry.)