

TAO-A Option Switch Settings: 1(Pulse/Single Price/ICT)

Supported bill US\$ 1, 5, 10, 20, 50, 100 6 bills.

TAO-A dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject US\$ 1	ON											
★ Accept US\$ 1	OFF											
★ Reject US\$ 5		ON										
★ Accept US\$ 5		OFF										
★ Reject US\$ 10			ON									
★ Accept US\$ 10			OFF									
★ Reject US\$ 20				ON								
★ Accept US\$ 20				OFF								
★ Reject US\$ 50 & 100					ON							
★ Accept US\$ 50 & 100					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / US\$ 1									OFF	OFF		
2 pulses / US\$ 1									ON	OFF		
4 pulses / US\$ 1									OFF	ON		
20 pulses / US\$ 1									ON	ON		
★ Interface Timing Conversion	50ms on / 50ms off										OFF	OFF
	60ms on / 300ms off										ON	OFF
	30ms on / 50ms off										OFF	ON
	150ms on / 150ms off										ON	ON

★ Manufacture setting

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(Single Price)

	INTERFACE	SW1	SW2	SW3	SW4
★	Single Price must be ON	ON			
	Not used	OFF			
★	Single Price Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(ICT)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	ICT Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting