

TAO-A Option Switch Settings: 1(Standard Pulse/NISR)

Supported bill US\$ 1, 5, 10, 20, 50, 100 6 bills.

TAO-A dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject US\$ 1	ON											
★	Accept US\$ 1	OFF											
	Reject US\$ 5		ON										
★	Accept US\$ 5		OFF										
	Reject US\$ 10			ON									
★	Accept US\$ 10			OFF									
	Reject US\$ 20				ON								
★	Accept US\$ 20				OFF								
	Reject US\$ 50 & 100					ON							
★	Accept US\$ 50 & 100					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / US\$ 1									OFF	OFF		
	2 pulse / US\$ 1									ON	OFF		
	4 pulse / US\$ 1									OFF	ON		
	20 pulse / US\$ 1									ON	ON		
★	Interface Timing Conversion	50ms on / 50ms off										OFF	OFF
		60ms on / 300ms off										ON	OFF
		30ms on / 50ms off										OFF	ON
		150ms on / 150ms off										ON	ON

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A TYPE Interface Settings: 2(Standard Pulse/NISR)

	INTERFACE	SW1	SW2	SW3	SW4	
★	Credit-Pulse Normal HIGH	ON				
	Credit-Pulse Normal LOW	OFF				
★	Pulse Mode		ON			
	NISR Mode		OFF			
★	Reserved			ON		
				OFF		
						ON
						OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4	
★	Reserved	ON				
		OFF				
	Pulse Mode		ON			
★	NISR Mode		OFF			
★	Reserved			ON		
				OFF		
						ON
						OFF

★ Manufacture setting